Technical specifications: **GMA200-MW16**



Display & control elements Status-LEDs: Display: Buttons: Alarm:	15 status LEDs for alarms, operating and relay states 2,2″ graphic display 5 buttons buzzer max. 100dB(A) adjustable		
		Environmental conditions Mounting:	only indoors up to an altitude of 2000m above sea level
for storage:	-25+60°C 099%r.h. (recommended: 0+30°C 4060%r.h.)		
for operation:	-20+55°C 099%r.h.		
Power supply	100 V to 240 Vac 50 Hz to 60 Hz mains voltage or/and 24 Vdc (20 Vdc to 30 Vdc)		
Operating voltage Ue:	through stabilized SELV or PELV power supply		
Power consumption:	max. 10W (without transmitter)		
	max. 90W (with transmitter)		
Fuse:	F1=T 500 mA (for GMA200)		
	F2=T 2.5A (for transmitter)		
Fransmitter connections			
Supply outputs:	24 Vdc \pm 3 % with built-in power supply, otherwise 20 Vdc to 30Vdc (see above)		
	16x 150 mA or Iges=0.6 A with different allocation		
Analog input signals I _{IN} :	4-20 mA or 0.2-1 mA		
	Tolerance*: ±0,3%MR@420mA or ±1,2%MR@0,21mA (MR=measuring range) Load approx. 50100Ω, Imax=70mA permanent / 500mA short time		
Digital signals TRM bus1+2:	RS485; Half-Duplex; max. 38400 Baud		
Measurement value processing			
Update time:	1s (If there are more than 16 transmitters and relay modules on the same TRM bus and the data transmission is only at 9600 baud, the cycle time is extended from 1.0 to max. 1.3 s, so that the time of 1 s cannot be maintained)		
Adjustment time for RS485:	Rise time t_{50} <2s or t_{90} <2sec Decay time t_{50} <2s or t_{10} <2sec		
for 420mA:	Rise time t_{50} <2s or t_{90} <4sec Decay time t_{50} <2s or t_{10} <4sec		
for 0,21mA:	$\label{eq:result} Rise time t_{50} < 6s \ or \ t_{90} < 10 sec \\ \end{tabular} Decay \ time \ t_{50} < 6s \ or \ t_{10} < 10 sec \\ \end{tabular}$		
	(extended by setting times of the gas measuring transmitters)		
Ready delay:	<40s (can be extended by running-in times of gas measuring transmitters)		
\S485 outputs			
RS485 outputs GMA bus:	RS485; Half-Duplex; max. 230400 Baud		
GMA bus:	(for GMA200 relay modules, control centre, PC, PLC or gateway)		
GMA bus: RS485 bus:	(for GMA200 relay modules, control centre, PC, PLC or gateway)		
GMA bus: RS485 bus:	(for GMA200 relay modules, control centre, PC, PLC or gateway)		
GMA bus: RS485 bus: telay outputs Contacts: Contact load capacity:	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC		
GMA bus: RS485 bus: telay outputs Contacts: Contact load capacity: Minimum switching current:	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA		
GMA bus: RS485 bus: Relay outputs Contacts: Contact load capacity: Minimum switching current: Minimum switching voltage:	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V		
GMA bus: RS485 bus: Relay outputs Contacts: Contact load capacity: Minimum switching current: Minimum switching voltage: Switching frequency:	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V max. 100 per year (per relay contact), valid for SIL applications according to EN 50402		
GMA bus: RS485 bus: Relay outputs Contacts: Contact load capacity: Minimum switching current: Minimum switching voltage:	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V max. 100 per year (per relay contact), valid for SIL applications according to EN 50402 Basic insulation between the relays: 1&2, 3&4, 5&6, 7&8		
GMA bus: RS485 bus: Relay outputs Contacts: Contact load capacity: Minimum switching current: Minimum switching voltage: Switching frequency:	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V max. 100 per year (per relay contact), valid for SIL applications according to EN 50402		
GMA bus: RS485 bus: Relay outputs Contacts: Contact load capacity: Minimum switching current: Minimum switching voltage: Switching frequency: Insulation clearances: Analogue outputs	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V max. 100 per year (per relay contact), valid for SIL applications according to EN 50402 Basic insulation between the relays: 1&2, 3&4, 5&6, 7&8 Double insulation between the relays: 2&3, 4&5, 6&7		
GMA bus: RS485 bus: Relay outputs Contact load capacity: Minimum switching voltage: Switching frequency: Insulation clearances: Analogue outputs I _{our} 1+2:	 (for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V max. 100 per year (per relay contact), valid for SIL applications according to EN 50402 Basic insulation between the relays: 1&2, 3&4, 5&6, 7&8 Double insulation between the relays: 2&3, 4&5, 6&7 4-20mA with linear transfer function (load max. 560Ω) 		
GMA bus: RS485 bus: Relay outputs Contacts: Contact load capacity: Minimum switching current: Minimum switching voltage: Switching frequency: Insulation clearances: Analogue outputs	(for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V max. 100 per year (per relay contact), valid for SIL applications according to EN 50402 Basic insulation between the relays: 1&2, 3&4, 5&6, 7&8 Double insulation between the relays: 2&3, 4&5, 6&7		
GMA bus: RS485 bus: elay outputs Contact load capacity: Minimum switching voltage: Switching frequency: Insulation clearances: malogue outputs I _{our} 1+2:	 (for GMA200 relay modules, control centre, PC, PLC or gateway) RS485; Half-Duplex; max. 38400 Baud (only for GMA200 relay modules) 8 relays with normally open contact 3A/250V AC or 3A/30V DC 10mA 5V max. 100 per year (per relay contact), valid for SIL applications according to EN 50402 Basic insulation between the relays: 1&2, 3&4, 5&6, 7&8 Double insulation between the relays: 2&3, 4&5, 6&7 4-20mA with linear transfer function (load max. 560Ω) 		



Technical specifications: **GMA200-MW16**



max. 2 GB microSD card with FAT formatting (FAT16)
Mini USB socket for device configuration with PC
IP65 in accordance with IEC 60529; IK08 in accordance with IEC 62262
Plastic
270 x 290 x 98 mm (W x H x D)
approx. 2kg
3-4 wire ≥0.75 mm ² LiYY, NYM (for GMA200 supply)
2-4 wire 0.5-1.5 mm ² LiYY, LiYCY (for transmitters)
2-wire 1x2x0,22mm ² BUS-LD (for GMA bus with length >10 m)
max. 20 x M16x1.5 (for cable diameter 3-7 mm respectively 5-10 mm)
0.08 mm2 to 2.5 mm ² cross-section
EN 50270:2015 (interference emission: type class I, interference immunity: type class II)
EN 61010-1:2010 (Pollution degree 2, overvoltage category II for mains supply)
(Pollution degree 2, overvoltage category III for relay contacts)
EN 50402:2017; IEC 61508-1 to -7:2010 (SIL2/SC3)
EN 50271:2018; EN 62061:2016; ISO 13849-1:2015
EN 60079-29-1:2016 (EX); EN 50104:2010 (OX); EN 45544-1/-2/-3:2015 (TOX)
20 years

* This is only the measurement tolerance of the GMA. The transmitters have additional tolerances.

